



8 Channels relay

Model: KW-RL8S

## Overview

Relay modules suitable for switching of higher voltages and perfect for use with microcontrollers including Door interface. The relays used are rated up to 10A and have NO/NC contacts. Each channel has an LED indicator to show the relay is on.

## Specifications

- Channels: 8, Active by High/Low selectable
- Connects directly to a microcontroller/ Door interface
- LED Indicator for each channel
- Dual Trigger design, using special two-way driver IC design
- Anti-jamming capability, using freewheeling diode protection
- Part of the relay contacts using double-sided bold wiring for large current through, safe and reliable.
- Each relay output leads to the normally open and normally closed two electric shock, easy to use and flexible.

## Technical Information

- 12VDC Power supply
- Switching Capacity: 10A
- Maximum Voltage: 250VAC / 30VDC
- Circuit board size 140mm X-55mm mounting hole size 133 mm X-40mm



Distribution by  
**Keyword Technologies & Services Co., Ltd.**

19 Soi BangkokNon 9/1 Bang Khen, Muang Nontaburi, Nontaburi, 11000 Thailand  
+66-81-913-0033